




OIL sensor emulator

(level, quality, temperature)

Mercedes, BMW, VAG

Purpose:

For Mercedes, BMW and VAG group cars. Original oil quality sensor emulator, emulates valid oil temperature, level and quality. 1st generation sensors covered (PWM modulation - **not** LIN / BSD !).



Installation:

+, - and signal wire (open collector output), pin meanings are marked on opposite side of board. Car brand you must select by placing solder joints (jumpers). There is a LED for control purposes mounted on emulator board.

Jumper settings:

- **BMW:** both jumpers open (no solder joints). LED: one short blink, continuously.
- **MERCEDES:** both jumpers shorted. LED: 3x short blinks, continuously.
- **VAG:** one of jumpers shorted, another one open (no matter which ones). LED blinks twice.

